




# Modulating Induced Draft System with VSUB 8/12 Blower, CPC-3 Controller and 115 volt VFD

12/02/04  
8052030 SHEET 1

**PROJECT:** \_\_\_\_\_

10' (3m) COMMUNICATIONS CABLE PROVIDED WITH EACH VFD







FIGURE 8052030 12/02/04



**WARNINGS:**

1. Improper wiring to the transducer will destroy the transducer. Use caution to ensure that the wiring to the transducer is correct before activating the CPC-3 controller.
2. Verify that the input power voltage matches the VFD's nameplate rating before applying power. Improper supply voltage to the VFD could damage the VFD.
3. Verify that the blower (VSub 8/12) is wired for the output voltage from the VFD. If not correct, severe damage to the blower and/or the VFD could result.
4. When the system is completely installed, perform the safety interlock and operational test as outlined in the installation manuals. Failure to do these tests could result in an unsafe and/or incorrectly operating system.

**CAUTIONS:**

1. All wiring must be in metal conduit (best) or shielded cable.
2. Route transducer wiring in metal conduit or use Belden Shield Cable #9939 or equivalent. Make sure the transducer wiring does not contain or cross line voltage wiring or undesired transducer performance may result.
3. Do not run the VFD's input power and output power wiring in the same conduit. Undesired VFD operation could result.

**NOTES:**

1. If the provided 10-foot, 10-wire VFD control cable is not long enough to meet the application needs, use caution to ensure that the connections from the VFD to the CPC-3 controller are correctly located. MB to MB, MC to MC, etc. In addition, reference the Wire Length Table.
2. Use caulking to seal the electrical box cover to the electrical box, and to seal the conduit holes to hole plugs.
3. If required, non-fused disconnects are to be supplied by the installer.
4. This blower is shipped from the factory wired for 460 VAC. Reconfigure the motor wiring at the motor for 230 VAC. See the Motor Label for details.
5. The 115 VAC VFD outputs 230, 3Ø power.